UNIVERSITI TEKNOLOGI MARA

NOVEL HEXANOYL CHITOSAN/ENR25 BLEND POLYMER ELECTROLYTES FOR APPLICATION IN ELECTRICAL DOUBLE LAYER CAPACITOR (EDLC)

NUR ASHEILA NADIRAH BINTI JAMALUDDIN

Thesis submitted in fulfilment of the requirements for the degree of **Doctor of Philosophy**

Faculty of Applied Sciences

June 2018

ABSTRACT

Hexanoyl chitosan soluble in THF is prepared by acyl modification of chitosan. Epoxidized natural rubber (ENR25) (25 mol%) is chosen to blend with hexanoyl chitosan. Elastic property of hexanoyl chitosan was enhanced with the incorporation of ENR25. DSV and DSC studies revealed immiscibility of hexanoyl chitosan and ENR25. DSC results also demonstrate the dissolution of salt was favoured in ENR25 phase. Single salt polymer electrolytes based on hexanoyl chitosan-ENR25 were prepared by employing LiN(CF₃SO₂)₂ or LiCF₃SO₃ as the doping salt. The electrolytes were prepared by solution casting method. Conductivity enhancement was observed in the blends as compared to the neat hexanoyl chitosan. The maximum conductivities achieved for LiCF₃SO₃ - and LiN(CF₃SO₂)₂ - comprising electrolyte systems were 1.6 x 10^{-8} and 5.0 x 10^{-7} S cm⁻¹, respectively. The conductivity of LiN(CF₃SO₂)₂ system is higher compared to LiCF₃SO₃ system due to different lattice energy of salts. Deconvolution of spectra bands in the $v_{as}(SO_2^-)$ mode of LiN(CF₃SO₂)₂ and $v_s(SO_3^-)$ mode of LiCF₃SO₃ has been carried out to estimate the relative percentage of free ions and associated ions. The findings were in good agreement with conductivity results. FTIR results suggested that LiN(CF₃SO₂)₂ interacted with hexanoyl chitosan and ENR25. The effect of EMImTFSI on the conductivity of hexanoyl chitosan/ENR25-LiN(CF₃SO₂)₂ is further investigated. Upon addition of 12 wt% EMImTFSI, a maximum conductivity of 1.3×10^{-6} S cm⁻¹ is achieved. Methods based on impedance spectroscopy and FTIR are employed to study the transport properties of the prepared polymer electrolytes. The ac conductivity of the EMImTFSI system was found to obey universal law, $\sigma(\omega) = \sigma_{dc} + A\omega^s$. The temperature dependence of exponent s is interpreted by the small polaron hopping (SPH) model. The optimized electrolyte was then used to fabricate the EDLC cell. The electrochemical stability for hexanoyl chitosan/ENR25-LiN(CF₃SO₂)₂-EMImTFSI was up to 2.7 V. The specific capacitance of the EDLC was calculated for various scan rates.

ACKNOWLEDGEMENT

First and foremost I praise to God for inspiring me, giving me strengths and opportunities to embark on my PhD and for completing this long and challenging journey successfully. My gratitute and thanks go to my supervisor Assoc. Prof Dr Tan Winie, and co-supervisor, Assoc. Prof. Dr Ab Malik Marwan Ali. Thank you for the support, patience and ideas in assisting me with this project. I also would like to express my gratitude to the staffs of the Institute of Science, Ionic Color Coating Laboratory, Polymer Blends Laboratory and Instrumentation Laboratory for providing the facilities, knowledge and assistance.

Special thanks to my colleagues and friends for helping me through past few years with this project. Finally, this thesis is dedicated to my family for their kind supporting me to finish my studies. This piece of victory is dedicated to them. Alhamdulilah.

TABLE OF CONTENTS

	Page		
CONFIRMATION BY PANEL OF EXAMINERS	ii		
AUTHOR'S DECLARATION	iii		
ABSTRACT	iv		
ACKNOWLEDGEMENT	V		
TABLE OF CONTENTS	vi		
LIST OF TABLES LIST OF FIGURES LIST OF SYMBOLS LIST OF ABBREVIATIONS	xi xiv xxii xxii xxvii		
		CHAPTER ONE: INTRODUCTION	1
		1.1 Research Background	1
1.2 Problem Statement	3		
1.3 Significance of Research	3		
1.4 Objectives of Research	3		
1.5 Scope of Research	3		
1.6 Thesis Outline	4		
CHAPTER TWO: LITERATURE REVIEW	5		
2.1 Polymer Blends	5		
2.2 Polymer Electrolytes	7		
2.3 Chitosan-Based Polymer Electrolytes	10		
2.4 Limitation of Chitosan-Based Polymer Electrolytes	12		
2.5 Hexanoyl Chitosan-Based Polymer Electrolytes	12		
2.6 Epoxidized Natural Rubber (ENR)-Based Polymer Electrolytes	15		
2.7 Lithium Salts	17		
2.8 Ionic Liquid (IL)	18		
2.9 Electrical Double Layer Capacitor (EDLC)	20		

25
25
25
26
26
26
27
27
28
29
30
31
32
35
37
38
40
40
42
47
47
47
48
50
50
50
50
52